



Scorpio & Icon Platform M+ Operational Guide

Legal Notices

Product specifications and features are subject to change without prior notification.

Copyright© 2019 Sound Devices, LLC. All rights reserved.

This product is subject to the terms and conditions of a software license agreement provided with the product, and may be used in accordance with the license agreement.

This document is protected under copyright law. An authorized licensee of this product may reproduce this publication for the licensee's own personal use. This document may not be reproduced or distributed, in whole or in part, for commercial purposes, such as selling copies or providing educational services or support. This document is supplied as a technical guide. Special care has been taken in preparing the information for publication; however, since product specifications are subject to change, this document might contain omissions and technical or typographical inaccuracies. Sound Devices, LLC does not accept responsibility for any losses due to the user of this guide.

Trademarks

The "wave" logo is a registered trademark. All other trademarks herein are the property of their respective owners.

Scorpio and Icon Platform M+ User Guide | Rev 1-A | 05/20/19

This document is distributed by Sound Devices, LLC in online electronic (PDF) format only. Published in the USA.

This table provides the revision history and cross-reference links to "what's new" in this guide.

REV #	DATE	VERSION	DESCRIPTION
1-A	05/19	A	V1.0



Post Office Box 576
E7556 State Rd. 23 and 33
Reedsburg, Wisconsin 53959 USA
www.sounddevices.com

+1 608.524.0625 main
+1 608.524.0655 fax
800.505.0625 toll free
support@sounddevices.com

Initial Setup

For access to all functionality, an Icon D2 display must be fitted to the Icon Platform M+

INSTALLING FIRMWARE

For optimal operation, Sound Devices recommends installing the Scorpio-specific Icon Platform M+ firmware available from the Sound Devices website: <https://www.sounddevices.com/product/scorpio/>

1. Download and install the iMap application here: <https://iconproaudio.com/product/platform-m-plus/>
2. Connect the Icon Platform M+ to the computer via USB, then turn on the M+.
Important: Due to the automatic update feature in iMap, you must disconnect from the Internet before launching the iMap application.
3. Launch iMap.
4. Click “Upgrade Firmware” and click OK in the ‘Firmware Upgrade v1.04 About to Start’ window then continue to follow the steps.

ADJUSTING PLATFORM M+ FADER TOUCH

SENSITIVITY

1. Press and hold encoder 2 while powering on the Platform M+ One or more Sel buttons will illuminate. The number of Sel buttons illuminated determines the touch sensitivity - 1 button illuminated is the most sensitive, 8 buttons illuminated is the least sensitive.
2. Rotate encoder 8 to set the desired sensitivity. It is recommended to set sensitivity such that only 1 Sel button is illuminated. If the small red LEDs by encoders 1 and 2 flash intermittently, the sensitivity is set too high.
3. Press encoder 8 to save the sensitivity setting.

ADJUSTING PLATFORM M+ FADER SPEED

1. Press and hold encoder 1 while powering on the Platform M+. The faders will start moving back and forth.
2. Rotate encoder 8 to set the desired speed.
3. Press encoder 8 to save the speed setting.

CONNECTION

1. Connect a 12-18 VDC power source to the DC In on the Platform M+ rear panel. DC connector is 5 mm width, center pin +ve.
2. Connect Scorpio’s USB-A port to the USB-B port on the rear of the Platform M+. You can also connect via a USB hub connected to the Scorpio’s USB-A port.
3. Power on the Platform M+
4. When the Scorpio initiates communication with the Platform M+, the Icon D2 displays ‘Sound Devices Scorpio Connecting ...’

Note: Once the Scorpio establishes connection with the Platform M+, faders and trims 1-12 are disabled on the Scorpio.

Mode Buttons - Mix, Bus, Out (Mixer, Read, Write)

MIX MODE

Press Mix (Mixer) button. This is the main default mode where mixing takes place.

The Bank Buttons switch between banks Ch 1-8, Ch 9-16, Ch 17-24, Ch 25-32.

FADER channel fader.

KNOB trim gain. Pressing the trim knob toggles between trim and pan adjustment.

SOLO channel PFL.

MUTE channel mute.

SEL opens the Scorpio channel screen. Knobs 1-8 change their function as follows:

Ch 9	Source	Delay	Limit	HPF-On	EQ Low	>>
Boom	M16-Ph	15mS	On	120Hz	0dB 6.8kHz	2.0Q

KNOB 1 Adjusts channel trim gain and displays channel name.

KNOB 2 Displays channel source. *Read only.

KNOB 3 Rotate to adjust delay. Press to toggle polarity.

KNOB 4 Press to toggle limiter on/off.

KNOB 5 Rotate to adjust HPF freq, press to toggle HPF on/off.

KNOB 6, 7, AND 8 Rotate to adjust EQ Gain, Freq and Q respectively.

PRESS KNOB 6 to toggle bypass for that band.

PRESS KNOB 7 to cycle between Low, Mid, and Hi bands.

PRESS KNOB 8 to switch between band or shelf (LF and HF only).

PRESS KNOB 6 >1 sec to bypass all bands. 'EQ Off' is displayed on top row.

NEXT BANK (press right Bank button) -> Knobs 1-8 = Rotate to adjust Bus send 1-8 gains respectively.

BUS MODE

Press Bus (Read) button to switch the panel to bus master faders 1-10, LR.

The Bank buttons switch between banks Bus 1-8 and Bus 9, 10, L, R.

FADER bus master gain.

MUTE mutes bus.

ARM arms bus. Only available on Bus 1, 2, L, and R.

SEL switches to sends-on-faders mode for the selected bus.

FADER channel send gain.

KNOB rotate to set channel routing to the bus [Off, Pre, Post, or Send].

SOLO press to PFL the channel.

MUTE press to mute the channel.

BANK BUTTONS switch between banks Ch 1-8, Ch 9-16, Ch 17-24, Ch 25-32.

9TH FADER bus master gain for the selected bus.

OUT MODE

Press Out (Write) button to switch the panel to output gains 1-10, LR, Hirose A and Hirose C.

The Bank buttons switch between banks X1-8 and X9-10, L, R, Hirose A, Hirose C.

FADER output attenuation.

MUTE mutes output.

Transport Controls

Rec, Stop, Play, <<, >> duplicate the functionality of Scorpio's transport joystick.

Menu (RTZ) Button

Press to access Scorpio's main menu and to back out of menus.

Sel and HP (Zoom) Buttons

The jog wheel has two mutually exclusive modes determined by the two buttons above it.

SEL (LEFT ZOOM) BUTTON jog wheel's rotate and press functions emulate Scorpio's Select encoder.

HP (RIGHT ZOOM) BUTTON jog wheel's rotate and press functions emulate Scorpio's HP encoder.

Com 1, Com 2, Slate (Chan) Buttons - Talk Back

COM 1 BUTTON activates/deactivates Com 1 send.

COM 2 BUTTON activates/deactivates Com 2 send.

COM 1 + COM 2 BUTTONS SIMULTANEOUSLY activates/deactivates Slate.

Lock Button

Pressing the lock button prevents motorized fader adjustments.

SOUND  **DEVICES**

Post Office Box 576
E7556 State Rd. 23 and 33
Reedsburg, Wisconsin 53959 USA

support@sounddevices.com

+1 608.524.0625 main
+1 608.524.0655 fax
800.505.0625 toll free

www.sounddevices.com