

XL-3

3.5mm to TA3F Cable



Description

The XL-3 is designed to connect Sound Devices mixers and recorders to various equipment.

Wiring

- TA3 pin-1: 3.5mm sleeve and cable shield (ground)
- TA3 pin-2: 3.5mm tip (left)
- TA3 pin-3: 3.5mm ring (right)

Specifications

- Cable: Belden 1800F
- TA3 plug: Neutrik
- 3.5mm TRS plug: Switchcraft
- 20-inch length

Linking Sound Devices Products

The XL-3 can be used to make the following connections:

Output	Input
<ul style="list-style-type: none"> • 552, 442, MixPre-D, MixPre, or 7-Series TAPE OUT (3.5mm) • 788T 5,6 output (3.5mm) 	<ul style="list-style-type: none"> • 442 or 302 MIX IN (TA3) • 552 or 442 RTN B (TA3)
<ul style="list-style-type: none"> • 302, 442, or 552 MIX OUT (TA3) 	<ul style="list-style-type: none"> • 552 or 442 RTN B (3.5mm) • 302 RTN / 4,5 input (3.5mm) • MixPre-D or MixPre TAPE RTN (3.5mm) • HX-3 STEREO/LOOP IN (3.5mm)
<ul style="list-style-type: none"> • MixPre-D ST UNBAL MIC OUT (TA3) 	<ul style="list-style-type: none"> • 3.5mm mic-level input on some consumer video cameras (Canon 5D, etc)