

CL-1

Remote Control and Keyboard Interface



Description

The CL-1 is a hardware accessory for 7-Series recorders. External alphanumeric keyboards (PS/2 type) and switch contacts (GPI) connect to the CL-1 and their actions are programmed within the 7-Series recorder setup menu.

The CL-1 is powered by the 7-Series through the C. Link port on the recorder...

How to Use

- Connect the CL-1 to the 7-Series C. Link input connection using the included C. Link cable.
- Program the keyboard and switch contact behavior from the 7-Series setup menu (complete documentation for CL-1 control is included in user guide of the 702, 702T, 722, 744T, and 788T).

Specifications

- Includes 6-foot C.Link Cable
- Filter dimensions 1.25" x 2" x 2" (H x W x D)
- Removable terminal block connector for the 6 programmable pins (pins 1 through 6)
- Pin-7 is common ground
- Pin-8 provides +5 V, 100 mA to power LED's
- The maximum cable length between CL-1 and recorder is 20 feet

Note

The CL-1 is powered and programmed from the 7-Series recorder.

Complete details on CL-1 programming and control are available in 7-Series User Guides.